

## METHOD AND APPARATUS FOR EQUALIZATION ACROSS PLURAL DATA CHANNELS

### CROSS-REFERENCE TO RELATED APPLICATIONS

This is the first application filed for the present  
5 invention.

## MICROFICHE APPENDIX

Not Applicable.

## TECHNICAL FIELD

The present invention relates to communications  
10 networks, and in particular to a method and apparatus for  
signal equalization across multiple data channels of an  
optical communications network.

## BACKGROUND OF THE INVENTION

In the modern communications network space, signal reach and spectral density are important factors in overall network cost. Assuming other factors to be equal, increases in either signal reach or spectral density tend to reduce overall network cost and are thus very attractive to network service providers.

Signal reach is the distance that an optical signal can be transmitted through a fiber, before conversion to electronic form is required to perform signal regeneration. Using suitable optical amplifiers and optical processing techniques, between 10 and 20 fiber spans (of 40-80 km each) can be traversed by an optical signal before optical/electrical conversion and regeneration are required.

Spectral density, which is normally expressed in terms of bits/sec/Hz (b/s/Hz), is a measure of the extent to which the theoretical maximum bandwidth capacity of an optical channel is utilized. This value is generally determined by dividing the line rate (in bits/sec.) of a channel by the optical frequency (in Hz) of that channel. A spectral density of 1 indicates that, for a given channel, the line rate and optical frequency are equal, so that each carries a bit of information. Existing telecommunications systems commonly operate at line rates of approximately 2.5Gb/s to 40Gb/s. At a line rate of 10Gb/s, current Wavelength Division Multiplexed (WDM) (or Dense Wave Division Multiplexed (DWDM)) transmission systems achieve a spectral density of approximately 0.1 b/s/Hz. If the line rate is increased to 40Gb/s, the spectral density increases to approximately 0.4b/s/Hz, illustrating the advantages of increasing the line rate.

However, there is a trade-off involved in using increased line rates to improve spectral density. In particular, increased line rates typically result in a reduction in signal reach. For example, with the use of appropriate optical amplifiers, a signal reach of 2500km has been demonstrated at a line rate of 2.488Gb/s (equivalent to a SONET/SDH OC-48 signal). At a line rate of 40Gb/s, the signal reach drops to approximately 1000 Km. This reduction in signal reach is explained by the fact that, as the line rate increases non-linear optical effects (e.g. self-phase modulation, optical dispersion, etc.) become progressively more significant, and cause increased bit error rates. In general, in order to keep the bit error rate below a tolerable threshold the distance that an optical signal is transmitted through a fiber before conversion to electronic form must be reduced.

003211"6EE22/60

Typically, the performance of optical fibers and amplifiers is non-linear across an optical spectrum of interest. This non-linear performance is manifested in, among other things, variations in the signal-to-noise ratio and signal gain (Q) of each channel. These variations tend to accumulate with each amplification stage and thus can become very large over the 15-20 spans of a fiber link. Since the length of each fiber link (i.e. the length of each span, and the number of spans before conversion to electronic form) is governed by the bit error rate of the lowest-performing channel, such high Q variations mean that most of the (higher performing) channels must operate with a shorter signal reach than would be indicated by their individual bit error rates. Accordingly, it is desirable to equalize performance across the channels.

Various methods of optical gain equalization are known in the art. See, for example, United States Patent No. 6,091,538 issued to Takeda et al. on July 18, 2000 and entitled Gain Equalizing Apparatus; and United States Patent No. 6,097,535 issued to Terahara on August 1, 2000 and entitled Method for Optical Amplification and System for Carrying Out the Method. Both of these patents use a variation of known Adaptive Optical Equalization techniques, in which the detected signal power is used to dynamically adjust the gain of an optical amplifier, to thereby minimize variations in the gain across multiple channels. Other known techniques involve the use of static or dynamic gain equalization filters, which operate by attenuating the optical signal power on channels with relatively high gain.

While each of the above methods are capable of reducing variations in gain, the physical properties of

003211 6622260

installed equalization devices are subject to a certain amount of variation, resulting in an unavoidable equalization error, typically on the order of approximately  $\pm 0.2\text{dB}$ . Over a link comprising 20 spans, this optical equalization error can accumulate to produce an uncompensated variation across the channels of as much as  $\pm 4\text{dB}$ .

Accordingly, a method and apparatus that enables maximized signal reach by providing effective equalization across multiple channels remains highly desirable.

## SUMMARY OF THE INVENTION

Accordingly, an object of the present invention is to provide a method an apparatus for conveying data signals through a multi-channel WDM network in which the effects of performance variations across the channels are effectively compensated.

Accordingly, an aspect of the present invention provides a method of optical equalization across N (an integer,  $N>1$ ) channels of a multi-channel link of a communications network. Each one of M (an integer,  $M>1$ ) parallel data signals are distributed across the N channels of the link, such that a substantially equal portion of each data signal is conveyed through each one of the N channels. Respective bit-streams received over the N channels are processed to recover the M data signals. As a result, performance variations between the N channels are optically equalized by averaging within each of the M data signals.

A further aspect of the present invention provides  
30 a method of conveying M (an integer,  $M>1$ ) data signals

062935Z JUL 78  
FM JCRC  
TO DIA  
INFO JCS  
SUBJ: RECENT ACTIVITY OF THE  
REPUBLICAN PARTY IN VIETNAM  
REF: JCRC REPORT DATED 1 JULY 1978  
PRIORITY: PRIORITY  
CLASSIFICATION: UNCLASSIFIED  
DOWNGRADING AND DECLASSIFICATION: UNCLASSIFIED  
AUTHORITY: JCRC REPORT DATED 1 JULY 1978  
CITE: JCRC REPORT DATED 1 JULY 1978  
1  
2  
3  
4  
5  
6  
7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814

across a multi-channel link of a communications network. At a transmitting end of the link, each one of the M data signals are distributed across the N channels of the link, such that a substantially equal portion of each data signal is conveyed through each one of the N channels. At a receiving end of the link, respective bit-streams received over the N channels are processed to recover the M data signals.

Another aspect of the present invention provides a system for equalization across N (an integer,  $N>1$ ) channels of a multi-channel link of a communications network. The system comprises: means for distributing each one of M (an integer,  $M>1$ ) parallel data signals across the N channels of the link, such that a substantially equal portion of each data signal is conveyed through each one of the N channels; and means for processing respective bit-streams received over the N channels to recover the M data signals. As a result, performance variations between the N channels are optically equalized by averaging within each of the M data signals.

Another aspect of the present invention provides an apparatus for enabling equalization across N (an integer,  $N > 1$ ) channels of a multi-channel link of a communications network, the apparatus comprising means for distributing  
25 each one of M (an integer,  $M > 1$ ) parallel data signals across the N channels of the link, such that a substantially equal portion of each data signal is conveyed through each one of the N channels.

Another aspect of the present invention provides a  
30 apparatus for enabling equalization across N (an integer,  
N>1) channels of a multi-channel link of a communications  
network, in which a substantially equal portion of each one

of M (an integer,  $M > 1$ ) data signal is conveyed through each one of the N channels, the apparatus comprising means for processing respective bit-streams received over the N channels to recover the M parallel data signals.

- 5           Each data signal may be a Forward Error Correction (FEC) encoded data stream.

10           In embodiments of the invention, each one of the M data signals may be distributed across the N channels of the link by: substantially evenly dividing each one of the M data signals into N respective sub-signals; and interleaving one sub-signal of each data signal into a respective one of the N channels. Division of each data signal may be accomplished, for each data signal, by: partitioning the data signal into a sequential series of data units having a predetermined size; and forwarding each successive data unit, in turn, to a respective one of the N sub-signals. Each data unit may have a size of one or more bits.

20           In embodiments of the invention, a respective unique identifier is inserted into a predetermined location of each sub-signal, prior to interleaving the sub-signal into a respective one of the N channels. In such cases, processing a bit-stream received over a respective channel may comprise searching the bit stream to locate the unique identifier.

30           One sub-signal of each data signal may be interleaved into a respective one of the N channels using a conventional sequential interleaving process. Thus, a data unit can be sequentially selected from one sub-signal of each data signal, and each selected data unit then forwarded, in turn, to the channel.

008211-622260

In embodiments of the invention, a respective bit-stream received over each one of the N channels may be processed by: dividing each bit-stream to recover a respective sub-signal of each data signal; and interleaving  
5 respective recovered sub-signals of each data signal to recover each one of the M data signals. Division of each bit-stream may be accomplished, for each bit-stream, by: partitioning the bit-stream into a sequential series of data units having a predetermined size; and forwarding each  
10 successive data unit to a respective one of N recovered sub-streams.

In cases where each sub-signal includes a predetermined unique identifier, partitioning the bit-stream may be accomplished by searching the bit-stream to locate the unique identifier; and extracting one or more data units associated with the unique identifier from the bit-stream.

A conventional sequential interleaving process may be used to interleave respective recovered sub-signals of each data signal to recover each one of the M data signals. Thus, for each one of the M data signals, one data unit can be sequentially selected from each sub-signal of the data signal, successively selected data units are then appended to recover the original data signal.

25       An advantage of the present invention resides in  
the recognition that it is the bit error rate of data  
signals being transported through a fiber link, rather than  
the bit error rate of any one channel, that should be  
determinative of link length. By distributing each data  
30 signal evenly across two or more channels, the bit error  
rate for the signal is an average of the bit error rates of  
each involved channel. Thus the impact of any variations

09-06-1978

in channel performance is shared equally by each of the data streams, thereby diluting the effects of the lowest-performing channel and consequently allowing an increase in link length beyond that which would be indicated by the bit error rate of the lowest-performing channel.

#### **BRIEF DESCRIPTION OF THE DRAWINGS**

Further features and advantages of the present invention will become apparent from the following detailed description, taken in combination with the appended drawings, in which:

Fig. 1. is a block diagram schematically illustrating a communications network in which an embodiment of the present invention may be deployed;

Fig. 2 is a block diagram schematically illustrating operation of a signal distribution unit 12 in accordance with an embodiment of the present invention, the signal distribution unit 12 being adapted to operate in a transmitting end node of a fiber link; and

Fig. 3 is a block diagram schematically illustrating operations of a signal regeneration circuit in accordance with an embodiment of the present invention, the signal regeneration circuit being adapted to operate in a receiving end node of a fiber link.

It will be noted that throughout the appended drawings, like features are identified by like reference numerals.

00821 622260



## DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

The present invention provides a method and apparatus for optical equalization to improve signal reach by distributing two or more data signals across two or more channels of an optical link. At a receiving end of the optical link, data-streams conveyed through each of the channels are processed to recover the original data signals.

FIG. 1 is a schematic diagram of a communications network 2 in which the present invention may be deployed. The network 2 includes a plurality of nodes 4a-e (which may be, for example, routers, cross-connects, regenerators or Add-Drop-multiplexors (ADMs)) interconnected by fibre links 6a-e. Each of the nodes 4a-e are preferably electro-optical nodes configured for wave division multiplex (WDM) and/or dense wave division multiplex (DWDM) transport of data traffic. For the purposes of the present invention, optical signals received at a node 4 from a fiber link 6 are assumed to be de-multiplexed and converted to electrical signals for signal regeneration and/or routing. Each fibre link 6a-e includes one or more fibre spans 8 coupled together by optical amplifiers 10. For the purposes of the present invention, optical signals received at an optical amplifier 10 from a fiber span 8 are assumed to be optically de-multiplexed and amplified without optical to electrical conversion.

Fig. 2 is a block diagram schematically illustrating operations of a signal distribution unit 12 in accordance with an aspect of the present invention. The signal distribution unit 12 may be implemented as hardware and/or software within each transmitting end node 4a-e. In a hardware implementation, the signal distribution unit 12

may be an application specific integrated circuit (ASIC), or may be incorporated into a larger ASIC such as, for example, a forward error correction (FEC) ASIC. In either case, the signal distribution unit 12 operates to

5 distribute M (where M is an integer, and  $M > 1$ ) data signals 14 (in the example shown in Fig. 2,  $M=3$ ) across N (where N is an integer, and  $N > 1$ ) channels 16 (in the example shown in Fig. 2,  $N=4$ ). The channels 16 can then be routed through conventional signal transmission circuits

10 (not shown) which perform electro/optical conversion and optical multiplexing of the channels 16 into the fiber links 6a-e in a manner known in the art. For example, known signal multiplexing methods may be utilized to multiplex the channels 16 onto respective different wavelengths

15 within the same WDM or DWDM fiber, respective wavelengths within two or more WDM or DWDM fibers, or respective single-wavelength fibers. With any of these approaches, it is also possible to use a Code Division Multiple Access (CDMA) encoding system to combine and transmit data signals

20 within the channels 16.

In general, the signal distribution unit 12 comprises at least M signal dividers 18a-c, and at least N interleavers 20a-d. Each signal divider 18a-c divides a respective data signal 14a-c into N sub-streams 22 (i.e.

25 one sub-stream 22 for each channel 16). As illustrated in Fig. 2, one method by which this may be accomplished is to divide each data signal 14 into a sequential series of data units 24 of a predetermined length. The length of each data unit is arbitrary, and may be as short as a single

30 bit. The signal divider 18 then forwards each successive data unit 24 of a respective data signal 14 to a respective one of the sub-streams 22, in turn, so that each sub-stream 22 includes a substantially equal proportion of

003211 6622260

the original data signal 14. Each sub-stream 22 from a data signal 14 is forwarded to a respective one of the interleavers 20a-b, so that each channel 16 carries one sub-stream 22 from (and thus a substantially equal portion of) each data signal 14.

Each interleaver 20, which may be implemented in hardware and/or software, comprises a sub-stream processor 19 and a sequential interleaving multiplexor 21. The sub-stream processor operates to insert a unique sub-stream identifier into each of the sub-streams 22 received by the interleaver 20, prior to their being interleaved into a respective channel 16. The sub-stream identifier serves to enable successful discrimination and separation of the sub-streams from a respective channel 16 at a downstream node 4. The sub-stream identifier preferably comprises a unique, n-bit word, which is inserted into a respective sub-stream 22 at a predetermined frequency. The length (i.e. number n of bits) of the sub-stream identifier, and the insertion frequency are implementation specific, and may be varied as required. In order to provide reliable identification of the sub-stream identifier at a downstream node 4, a sub-stream identifier of at least 10 bits is preferred. In a high-noise environment, a sub-stream identifier of 20 bits or more may be required in order to obtain reliable separation of the sub-streams 22. Additionally, it is preferable to ensure that the insertion frequency of the sub-stream identifier is sufficiently high to enable accurate compensation for noise and signal jitter, but should not be so high as to introduce an unnecessary overhead into the sub-stream. In general, an insertion frequency of about 8kHz should yield satisfactory results in most cases.

008211"6EE22/60

The Sequential interleaving multiplexor 21 operates in a manner known in the art to interleave the sub-streams 22 (including their respective sub-stream identifiers) into a respective channel 16. The order in which bits of each sub-stream 22 are interleaved into a respective channel 16 is predetermined, to facilitate recovery of the original data signals 14 at a receiving end node 46.

In the embodiment illustrated in Fig. 2, the signal distribution unit 12 is configured to distribute  $M=3$  data signals 14a-c across  $N=4$  channels 16a-d. Thus the signal distribution unit 12 of Fig. 2 comprises  $M=3$  signal dividers 18a-c, each of which divides its respective data signal 14 into  $N=4$  sub-streams 22. Similarly,  $N=4$  interleavers 20a-d are provided for interleaving respective sub-streams 22 from each data signal 14 into a respective one of the channels 16. Thus, interleaver 20a operates to interleave sub-stream U1 of each of incoming data signals 14a-c to create a serial composite data-stream 26a on channel 16a. Interleaver 20b operates to interleave sub-stream U2 of each of incoming data streams 14a-c to create a serial composite data-stream 26b on channel 16b. Interleaver 20c operates to interleave sub-stream U3 of each of data streams 14a-c to create a serial composite data-stream 26c on channel 16c. Finally, interleaver 20d operates to interleave sub-stream U4 of each of data signals 14a-c to create a serial composite data-stream 26d on channel 16d.

As mentioned above, the number (M) of data  
30 signals 14, and the number (N) of channels are arbitrary  
within a range governed by physical constraints of the  
networks. Thus, it will be appreciated that the signal

000211 622260

distribution unit 12 of Fig. 2 may be equipped with a number of signal dividers 18 required to handle a desired number of data signals 14. Similarly, the distribution unit 12 is equipped with a number of interleavers 20 interconnected with the signal dividers 18, to distribute data signals 14 across a desired number of channels 16. Advantages of the present invention may be obtained with distribution across as few as two channels 16. However, in practice, it will generally be preferable to distribute 2 or more signals across a larger number of channels which, depending on the specifics of a particular implementation, may be less than, equal to, or greater than the number of data signals 14. The method and apparatus of the invention are transparent to the protocol of the data signals 14, and so the protocol may be selected as required for a specific implementation. For example, if desired the data signals 14 may be forward error correction (FEC) encoded SONET/SDH signals.

The signal distribution process described above with respect to Fig. 2 is fully reversible to recover the original data signals 14. Fig. 3 is a block diagram of a signal recovery unit 28, which is implemented in each receiving end node 4a-e. The signal recovery unit 28 shown in Fig. 3 can be implemented in hardware and/or software downstream of conventional optical demultiplexing and opto/electrical conversion circuits, which operate to optically demultiplex the channels 16a-d from a fiber link 6, and convert each composite data-stream 26a-d into electronic form for processing. Conventional clock recovery and signal regeneration circuits (not shown) may also be implemented upstream of the signal recovery circuit 28 shown in Fig. 3.

The signal recovery unit 28 generally includes at least N parallel elastic buffers 30a-d, each of which is arranged to receive a respective composite data-stream 26 from one of the channels 16. The elastic buffers 30a-d cooperate to de-skew the composite data-streams 26a-d, and thus compensate for propagation delay differences between each of the channels. Each of the de-skewed composite data-signals 26a-d is then passed to a respective framer 32 and demultiplexor 34. The framer 32 analyses the respective composite data-stream 26 to detect the sub-stream identifiers of each of the sub-streams 22 contained in the composite data-stream 26, and generates a synchronization signal which is used to control the operation of the respective demultiplexor 34. Using the synchronization signal, in combination with the known interleaving sequence of the interleavers 20a-d, each demultiplexor 30a-d operates to demultiplex its respective composite data-stream 26, to recover one sub-stream 22 of each data signal 14. The sub-streams 22 of each data signal 14 are forwarded (one from each demultiplexor 30) to a one of M multiplexors 32a-c which multiplex the sub-streams 22 to recover the respective data signals 14.

As shown in Figs. 2 and 3, a data stream 14 (which may be FEC encoded) is evenly divided into sub-streams 22, which are interleaved and transmitted through a fiber link within respective parallel channels 16. At a receiving end node 4b, the sub-streams 22 are demultiplexed from their respective channels 16 and then multiplexed together to recover the original data signals 14. Between transmitting and receiving end nodes 4, each composite data-stream 26 transits a fiber link 6 within a respective one of the N channels 16. Consequently, each composite data-stream 26 is subject to optical amplification gain, attenuation,

dispersion and noise in accordance with the optical performance of the channel 16 through which it is conveyed. When the composite data-streams are demultiplexed, the respective sub-streams 22 express a bit error rate that is associated with the optical characteristics of the channel on which it was conveyed.

Multiplexing of the sub-streams 22 in the signal recovery circuit 28 by sub-stream multiplexers 32 yields a recovered data signal 14 having an aggregate bit error rate that approximates an average of the bit error rates of each channel 16 through which the composite data-streams 26 were transmitted. Since each of the transmitted data signals 14 are preferably equally distributed over the respective channels 16, this averaging of bit error rates affects each of the data signals 14 approximately equally. Thus, optical equalization across the N channels of the fiber link 6a is achieved by averaging the effects of optical performance variations across M parallel data signals conveyed through the link 6.

The present invention therefore provides a method and apparatus for achieving optical equalization across multiple channels of a multi-channel fibre link 6a, thereby extending signal reach by distributing the effect related to channel performance.

The embodiment(s) of the invention described above is(are) intended to be exemplary only. The scope of the invention is therefore intended to be limited solely by the scope of the appended claims.

00221" 6EE22/60